

# IKD 1

# **Digital I/O Expansion Board**

### **APPLICATIONS**

The IKD 1 is a smart solution to increase numbers of digital I/O's to Woodward easYgen and DTSC-200 series controllers. It is possible to connect one or more IKD 1 units to the power management controllers (see table *Related Products* below).

Each of the inputs can be assigned a name, alarm class, NO/NC configuration and time delay. The name and class are displayed on the connected genset controller's display.

The IKD 1 output relays are controlled over the CAN bus connection from the main genset controller. Configuration of the IKD 1 is performed through the relay manager in the main controller and transmitted to the IKD 1.

A direct configuration cable (DPC) and software can be purchased for use with a PC or laptop and may be advisable for extensive configuration applications or where several similar units are to be set up.

### **Related Products**

	max. # of IKD	1
<ul><li>easYgen-1000 series</li></ul>		2
• easYgen-2000 series		2
<ul> <li>easYgen-3100P1/320</li> </ul>	0P1	2
easYgen-3100P2/320	0P2	4
<ul><li>easYgen-3400/3500P</li></ul>	<b>'1</b>	4
<ul><li>easYgen-3400/3500P</li></ul>	2	2
easYgen-3000XT (GC	C-3400XT-P1)	4(2)
<ul> <li>DTSC-200 and -200A</li> </ul>		2

- Digital output expansion module IKD-OUT-16 (Product Spec #37954): P/N 8440-2305
- Digital input expansion module IKD-IN-16 (Product Spec #37955): P/N 8440-2304

### **DESCRIPTION**

#### **Features**

- 8 configurable discrete alarm inputs
- 8 configurable FORM C relays with potential free contacts
- Configurable delays for each input
- CAN bus communication
- The discrete inputs transfer their status via CAN bus to the control unit.
- The control unit evaluates the status of these discrete inputs coming from the IKD 1 and depending on the configuration of the control unit, will take the appropriate action.
- The control unit can send commands via the CAN bus to remotely control the output relays of the IKD 1.
- The IKD 1 can be used with other manufacturer's controllers. Consult product manual 37135 for information regarding the address assignments of the CAN bus interface.

#### **Product Number P/N**

• 8440-2116


- 8 discrete inputs
- 8 relay outputs FORM C
- PC configurable<sup>1)</sup>
- CAN bus communication
- Microprocessor technology for accurate, repeatable and reliable operation
- CE marked
- UL/cUL Listing

<sup>1)</sup> Use software *LeoPC* for configuration

# **SPECIFICATIONS**

Power supply	CAN interfaceisolatedInsulation voltage (continuously)100 VacInsulation test voltage (≤ 5 s)1,000 VacVersionCAN bus
Discrete inputs isolated	Housing
Input range	DIN-rail mountingextrusion profile Um 122
	to snap-on on a DIN rail/C-profile
	168 × 128 × 51 mm
Relay outputsisolated	
Contact materialAgCdO	Connectionscrew/plug terminals 2.5 mm <sup>2</sup>
Load (GP)2.00 Aac@250 Vac	
2.00 Adc@24 Vdc / 0.36 Adc@125 Vdc / 0.18 Adc@250 Vdc	Weightapprox. 360 g
Pilot duty (PD)	Protection systemIP 20
1.00 Adc@24 Vdc / 0.22 Adc@125 Vdc / 0.10 Adc@250 Vdc	
	Disturbance test (CE) tested according to
Service interface	applicable EN guidelines
VersionRS-232	

# **DIMENSIONS**



08 41 42 08 38	Relay 8			et for the PC configuration ated on the top of the unit. This is where the DPC has to be plugged in.	
37 38 39 4	Relay 7				
35 36 38 38 38 38 38 38 38 38 38 38 38 38 38	Relay 6	ırd)	CAN bus	CAN-H CAN-L GND	16   17   18
31 32 33	Relay 5	on Boa	N/C	CAN-H CAN-L	13 14 15
28 29 30	Relay 4	xtensic	Digital input 8  Digital input 7  Digital input 6	8 <b>本</b> 7 <b>本</b> 6 <b>本</b>	10   11   12
25 26 27	Relay 3	I/O E	Digital input 5 Digital input 4 Digital input 3	5 ×4 4 ×4 3 ×4	7 8 9
22 23 24 S S S S S	Relay 2	KD 1 (Digital I/O Extension Board)	Digital input 2 Digital input 1 Common	2 1	4 5 6
19 20 21 NO NO	Relay 1	IKD 1	0 V DC 0 V DC 12/24 V DC	_	1 2 3

Subject to technical modifications.

2002-11-07 | IKD 1 Wiring Diagram ikd1ww-4502-ap.skf



#### CONTACT

North & Central America

Tel.: +1 (208) 278 3370

South America

Tel.: +55 19 3708 4800

Europe

Tel.: +49 711 78954 510

Middle East & Africa

Tel.: +971 2 678 4424

Russia

Tel.: +49 711 78954 515

China

Tel.: +86 512 8818 5515

India

Tel.: +91 124 4399 500

**ASEAN & Oceania** 

Tel.: +49 711 78954 510

**SALES SUPPORT** 

industrial.sales PG@woodward.com

**TECHNICAL SUPPORT** 

www.woodward.com

Subject to alterations, errors excepted.

Subject to technical modifications.


This document is distributed for informational purposes only. It is not to be construed as creating or becoming part of any Woodward Company contractual or warranty obligation unless expressly stated in a written sales contract.

We appreciate your comments about the content of our publications. Please send comments including the document number below to stat-doc@woodward.com

© Woodward All Rights Reserved

For more information contact:

## TYPICAL APPLICATIONS



The digital inputs are read by the IKD 1 and transferred via the CAN bus to the control unit (incl. alarm class). Each alarm input may have a delay as well as the control logic (NO/NC) configured individually during set up. The status of the alarm input is monitored in the control device and will show the alarm text in its display. The alarm class assigned in the control device evaluates the alarm input and reacts accordingly.

The control device's relay manager controls the IKD 1 relays. The control logic for each IKD 1 relay can be programmed individually in the control device. Logical commands can be configured using internal events as well as the status of the digital inputs coming from the IKD 1.

If a discrete input on the IKD 1 is enabled, the control device displays a text message and the control functions of the alarm class are executed (refer to all manuals relating to the control device). The control device must operate the IKD 1 relays.